



PS MANUAL

BCS-BATTERY CHARGERS

1.0 Model **BCS-A1204**

2.0 Description

12 Volt 4Amp SmartCharger Battery Charger



Durst Industries Australia Pty. Ltd.

durst.com.au

Phone: +61 2 9660 1755

Unit 1, 11 Packard Avenue
Castle Hill NSW 2154 Australia





3.0 Features

- Fully Automatic, Fast and Safe.
- Overcharging Protection.
- Short Circuit Protection
- High Efficiency
- Three stage Charging indicator LED's
- Eliminates Sulphation
- Compact and Lightweight
- Leads and Battery Clamps
- Australian Electrical Standard & EMC Compliant
- Available with Optional plug to suit Mobility Scooters, wheel chairs etc

4.0 Physical and Dimensional Properties

- Each unit weighs approximately 0.5 Kg
- Width 70 mm
- Length 155 mm
- Height 48 mm
- Carton Dimensions: 240 x 190 x 55
- Colour: Red

5.0 Performance

- Voltage 100-240 Volt
- Frequency 47-63 Hz
- Output Current: 4 Amps
- Boost Voltage 14.1 Volts
- Float Voltage 13.7 Volts
- Wattage: 58W
- Battery size Ahr 16 Ahr - 40 Ahr

6.0 Uses

- SmartCharger Battery Charger.
- Suitable for Automotive, Marine, Mobile Home or Caravan, Mobility Appliances, Golf Carts, Solar, Deep Cycle, UPS Standby.

7.0 Documentation

- Bar Code Number: **9346080001407**
- Product Specification Manual – PS 153
- Work Instruction Manual - WI 153
- Product Costing Manual - PC 153

