



PS MANUAL

CURRENT CLAMP

1.0 Model **MM-CA600**

2.0 Description

Inductive Current Clamps for Multimeters and Scopes



Durst Industries Australia Pty. Ltd.

durst.com.au

Phone: +61 2 9660 1755

Unit 1, 11 Packard Avenue
Castle Hill NSW 2154 Australia





PS MANUAL

3.0 Features

- Can be used with any Multimeter that has 200mV & 2V range and an input impedance of at least 1 M Ω
- LED light to inform you that the CA600 is turned ON
- Zero adjustment knob allows compensation for hysteresis effect in DC measurement
- Low Battery indication
- Jaw Opening Capability 30mm Conductor
- Overload protection 80 Amps for 60 seconds maximum

4.0 Physical and Dimensional Properties

- Each unit weighs approximately 0.24 Kg
- Width 67 mm
- Length 34 mm
- Height 190 mm

5.0 Performance

- Current Range: 0 to 600 Amps
- Accuracy:
 - DC Amps $\pm 2\% + 2A$
 - AC Amps $\pm 3\% + 2A$ (50Hz - 400 Hz)

6.0 Uses

- Ideal for capturing waveforms from fuel pumps, injectors and relays.

7.0 Documentation

- Bar Code Number: **9346080001799**
- Product Specification Manual – PS 192
- Work Instruction Manual - WI 192
- Product Costing Manual - PC 192

Durst Industries Australia Pty. Ltd.

durst.com.au

Phone: +61 2 9660 1755

Unit 1, 11 Packard Avenue
Castle Hill NSW 2154 Australia

