



# Durst Load Bank

## LBT-48-288B

Durst mobile switched load bank, offering maximum capacity with ease of use.

### Features:

- A true portable high capacity load bank
- Digital meters Volt & Amp (240 Vac 15meter lead supplied)
- Fan cooled
- 100% duty cycle
- Nominal voltage 24, 36, 48 Volts DC
- Nominal Amps Switching 12 Position 0-288 Amps  
Switch 1. 6 position of 24 amps each Total 144 Amps DC  
Switch 2. 6 position of 24 amps each Total 144 Amps DC
- Internal wiring high temperature silicone
- Suitable for Aviation, Defence, Solar, UPS system, Motive Power etc
- Powder coated steel cabinet
- Pneumatic wheels 250mm Diameter
- Side lifting eyes ( Not shown in Photo )
- Fold away side handles
- Fully insulated clamp, colour coded
- Designed in Australia for Australian conditions & climate
- Custom Built to your requirements as requested
- Models available for other voltages and currents
- Carry version available upon request
- More Load for your \$
- Size W=510mm D=550 H=1020 ( 1250 Including handle )

### Optional Features

- Anderson plugs & Sockets
- Terminals for Amp leads
- Analogue Volt meter with dual sprung movement
- Analogue Amp meter with dual sprung movement



DURST MOTOR & ELECTRIC INDUSTRIES P/L 189-189B ST JOHNS RD, GLEBE NSW 2037  
Ph: 02 9660 1755 Fax: 02 9692 0251 Email: [sales@durst.com.au](mailto:sales@durst.com.au) Web: [www.durst.com.au](http://www.durst.com.au)

LBT-48-288B Custom.doc